

Hand-Held Remotes (Flat Profile)



Stylish, modern appearance, with a luxurious piano lacquer finish in black or white, Motolux hand-held remotes come in single and multi-channel formats for complete versatility. These remotes also include the Show/Hide channels function, which allows unused channels to be disabled for simpler operation.

Product Specifications				
	Single Channel Remote	11 Channel Remote	16 Channel Remote	16 Channel Remote Rechargeable
Part Number:	801130001 (White) 801130890 (Black)	801230001 (White) 801230890 (Black)	8012512001 (White) 8012512890 (Black)	8012514001 (White) 8012514890 (Black)
Supplier Number:	MRT04-01W (White) MRT04-01B (Black)	MRT04-06W (White) MRT04-06B (Black)	MRT04-16W (White) MRT04-16B (Black)	MRT04-16LW (White) MRT04-16LB (Black)
Channels:	1 Channel	11 Channels Default setting of 6 channels, 5 to be unlocked	16 Channels (Digital)	16 Channels (Digital)
Voltage:	3.7v Lithium Battery			
Expected Battery Life:	>3 years for normal usage			Up to 1 year on a single charge for normal usage
Power Source:	1x CR2032 (Batteries included)			Charge via Micro USB Cable (not included)
Available Colours:	Available in White and Black			
Radio Frequency:	433 MHz works with all Motolux RF motors			
Operational Range:	80mtr outdoors (line of sight) / 30mtr indoors			
Show / Hide Channels:	Yes			
Transmitting Power:	≤10mW			
Working temperature:	-20C to +55C			
Mounting:	Magnetic Wall Mount with stick on Back Plate			

Instructions to Hide / Show / Unlock Channels

1. Press briefly (very quick push) the setting button found on the side or back of the remote control. The channel number will start to flash.
2. Use the left/right selection buttons to scroll through the channels from 1 to 16.
3. Go to the channel that you wish to Hide or Unhide.
4. Press the STOP (middle) button to unhide or hide a channel, you will notice the channel number will flash rapidly indicating that channel is now hidden or the channel will Flash Slowly to indicate that it is visible.
5. Press briefly (very quick push) the setting button found on the back of the remote control to exit the setting mode.



Motolux creates world-class motorisation products and systems, dedicated to window covering markets worldwide. Designed to enable fully integrated motorisation solutions, Motolux products are suitable for commercial or residential use. Our product range is streamlined to simplify the process of manufacturing, installation and ongoing maintenance of all major types of motorised window covering products.

REVISION 2 - 2021

MOTOLUX
Ordering Information
Australia / New Zealand
61 (0)3 9876 0400
sales@motolux.com.au
www.motolux.com.au